

Operating Instructions

Please read over the Q & A section to help you with the normal operation of this product.

"How will I distinguish if it a regular telephone call or my door?"

The DoorBell Fon™ will ring the telephones with a distinctive ring for each of its entryways. Both the D1 & D2 position will sound differently from a regular telephone call.

"How do I answer the door or gate?"

Simply pick up your telephone. You will be automatically connected with the doorbox. Even if you have 2 doorboxes connected just pick up the telephone the controller will determine which doobox is calling.

"What if I pick up the telephone after it has stopped ringing?"

The DoorBell Fon™ will ring through 3 ring cycles. If you miss picking up the phone during those rings, there will be approximately 20 seconds available for you to pick up the telephone and be automatically connected to the doorbox. If you pick up the telephone and you hear a dial tone, just hit the flash key or hook switch your telephone and you will be connected to the doorbox. *(There are optional 1 or 8 ring chips available)*

"What if I am on the telephone when someone comes to the door?"

The DoorBell Fon™ has built in call waiting? If you are on the telephone and a visitor pushes the doorbox button you will hear a distinctive call-waiting tone. You can place the call on hold by pressing the flash key or hook switching your receiver. This will place the call on hold and transfer you to the doorbox. When you are done talking to the door you can transfer back to your call by pressing the flash key or hook switching back.

"Will the DoorBell Fon™ affect my answering machine?"

The DoorBell Fon™ will not affect the operation of you answering machine. However you may use you answering machine to answer your door or gate. The DoorBell Fon™ will ring your telephones through a 3-ring cycle. You can set your answering machine to answer on 2 rings and leave messages for your visitors, as well as let them leave messages for you from your door.

"Can the DoorBell Fon™ open my door or gate from me?"

Yes, with the purchase of a ***Outbound trigger relay #DP-28SW*** you can trigger any type of electrical device from the (*) key on your telephone.

"How many telephones can I connect to the DoorBell Fon?"

There is no specific number of telephones. The amount will be based on the REN (Ringer Equivalency Number) of all the devices on your telephone line. The maximum operating range for the DoorBell Fon™ is 4.6-5.0. You can calculate this number by looking at the labeling on the bottom of your telephones, caller ID units and answering

machines. If you exceed the maximum allowed number then you may need a ring booster. You can contact ACNC customer service for further information.